

Recessed Housing Compatibility Information for the LR6 Downlight Family*

Manufacturer	Compatible	Compatible with Modifications	
Capri Lighting	CR1NB CR1NBQP CRR1NB CRR1NBQP QL1NB QL1NBQP	CIND6 ¹ CR1 ¹ CR1QP ¹ CRR1 ¹ CRR1QP ¹ PR1 ¹	PR75ASIC ¹ PR75IC ¹ QL1 ¹ QL1QP ¹ R150ASIC ¹
Con-Tech Lighting		RL30-IC ¹ RL30-ICSA-R ¹ RL38 ¹	RL38-ICER ¹ RL38-ICERSA ¹
Cree LED Lighting	RC6-12W RC6-12W-GU24		
Elco Lighting		EL7ICA ¹	
Halo (Cooper Lighting)	H7ICATNB H7ICTNB H7T	H7ICAT ¹ H7ICT ¹ H7TCP ¹ H7UICAT ¹	H7RICAT ¹ H7RT ¹ H7RICT ¹
Juno Lighting Group		IC2 ² IC22 ³ IC22R ⁴ IC22W ⁴ IC23 ²	IC2W ² TC2 ² TC2R ² TC2W ²
Lightolier		1104IC ⁵ 1104ICN ⁵	1104ICR ⁵
Lithonia Lighting	L7X L7XR LC6		
Liton Lighting	LH7-LLF	LH7IC-LLF ¹	LH7R-LLF ¹
Progress Lighting		P821-AT ⁶	P87-ATQC ⁶
Sea Gull Lighting		1107 ⁷ 1108 ⁷ 1118 ⁷	1128 ⁷ 1128QC ⁷
Quorum International		903 ¹	

Modification Notes:

- 1: Remove "L" bracket (and backing plate). Unclip Edison socket from bracket (or backing plate).
- 2: Loosen two socket bracket screws and turn socket bracket to free it. Bend side tabs down slightly.
- 3: Remove socket bracket by removing two mounting screws.
- 4: Loosen socket bracket screw and turn socket bracket to free it. Bend side tabs down slightly. Loosen backing plate slide nuts. Pry backing plate slide over slide stops. Bottom out backing plate.
- 5: Remove socket assembly from can. Bend short clips back.
- 6: Remove Edison socket from spring clips. Bend back or cut spring clips.
- 7: Remove socket bracket wing nut and screw. Remove socket bracket. Unclip socket from bracket.

* Compatibility was determined based on whether the LR6 would fit within the identified can when appropriately modified. The presence of a can on the compatibility chart is not a guarantee or warranty of the compatibility of the LR6 in any particular installation. The absence of a can from the compatibility chart does not indicate that the LR6 is not compatible with a particular can. In any install, the installer should make sure that the LR6 is securely retained in the housing at the time of install.



Cree LED Lighting
Morrisville · NC · 27560 · USA
1-919-287-7700
Fax 1-919-991-0730
www.CreeLEDLighting.com