

Linear LED T8 Lamp

Compatible for use with fluorescent T8 and T12 ballasts

2', 3' and 4' Specification



Energy Savings over 40-50% when compared to existing fluorescent T8 and T12 electronic and magnetic ballasted fixture applications.

For additional energy savings of 20 to 30% use with low ballast factor ballast or lighting control system.

Installation is easy and saves money. Just change the existing fluorescent lamps without the need to rewire the light fixture.

Install LED lamp using existing fluorescent ballast. Lamp can operate using optional 120-277VAC LED driver.

LED lamp models available in 3000k, 3500k, 4000k and 5000k color temperatures to support 2', 3', 4', 8', U-Bend and TTL/BIAX applications.

Expanded Versatility using

Quick-Fit™ Installation Technology

An LED T8 direct replacement lamp, requiring NO Re-WIRING of the light fixture, providing excellent energy savings when replacing T8 (32W) and T12 (34 and 40W) fluorescent lamps. Installation is easy...just remove existing fluorescent lamp and install the LED linear lamp.

Multi-Op™ (multi-Operation) LED lamp design works with most ballast types including T8 Electronic Instant Start, T8 Program Start Electronic and T12 Magnetic ballasts.

The Multi-Op™ LED product is the most versatile LED linear lamp on the market today. The LED Multi-Op™ linear lamp is also compatible with most existing fluorescent battery back-up ballasts.

If the existing ballast fails just replace the ballast or operate the LED lamp with the optional 120-277VAC LED remote driver.

Benefits:

- Light distribution angle of 270 degrees
- Excellent for low temperature applications
- High Performance DLC qualified models available
- Use with occupancy sensors with frequent starting
- Dimmable (with compatible driver / ballast)
- No glass or mercury for safer work environments
- Vibration and impact resistant
- Less lumen depreciation compared to fluorescent systems
- Instant ON operation
- Suitable for damp locations (avoid applications with direct water contact)
- Meets UL standard 1598c
- Long life product (>50,000 hours)
- Rotatable end caps for refrigeration and shelf lighting applications (optional)
- 5 Year manufacturer's warranty



Linear LED T8 Lamp

Compatible for use with fluorescent T8 and T12 ballasts

2', 3' and 4' Specification

Specifications:

Performance with different ballast types	Type	Installation T8 IS Electronic ballast		Installation T8 Program Start Electronic ballast		Installation T12 Magnetic ballast	
		Lumens	Average System Watts	Lumens	Average System Watts	Lumens	Average System Watts
Model #							
LEDT8-8-850-B-xSC	LED 2' T8	1145	9.30	1145	9.60	1380	14.00
LEDT8-8-840-B-xSC	LED 2' T8	1120	9.30	1120	9.60	1360	14.00
LEDT8-8-835-B-xSC	LED 2' T8	1100	9.30	1100	9.60	1340	14.00
LEDT8-8-830-B-xSC	LED 2' T8	1090	9.30	1090	9.60	1340	14.00
LEDT8-8-850-B-FHF*	LED 2' T8	945	9.30	945	9.60	1180	14.00
LEDT8-8-840-B-FHF*	LED 2' T8	920	9.30	920	9.60	1160	14.00
LEDT8-8-835-B-FHF*	LED 2' T8	900	9.30	900	9.60	1140	14.00
LEDT8-8-830-B-FHF*	LED 2' T8	890	9.30	890	9.60	1140	14.00
LEDT8-12-850-B-xSF	LED 3' T8	1250	13.00	1250	13.00	-	-
LEDT8-12-840-B-xSF	LED 3' T8	1225	13.00	1225	13.00	-	-
LEDT8-12-835-B-xSF	LED 3' T8	1150	13.00	1150	13.00	-	-
LEDT8-12-830-B-xSF	LED 3' T8	1150	13.00	1150	13.00	-	-
LEDT8-17-850-B-xSC	LED 4' T8	1900	17.50	1900	18.00	2550	31.0
LEDT8-17-840-B-xSC	LED 4' T8	1800	17.50	1800	18.00	2550	31.0
LEDT8-17-835-B-xSC	LED 4' T8	1700	17.50	1700	18.00	2150	31.0
LEDT8-17-830-B-xSC	LED 4' T8	1750	17.50	1750	18.00	2150	31.0
LEDT8-17-850-B-FHF*	LED 4' T8	1785	16.8	1785	17.00	2500	31.0
LEDT8-17-840-B-FHF*	LED 4' T8	1700	16.8	1700	17.00	2200	31.0
LEDT8-17-835-B-FHF*	LED 4' T8	1683	16.8	1683	17.00	2100	31.0
LEDT8-17-830-B-FHF*	LED 4' T8	1660	16.8	1660	17.00	2100	31.0
LEDT8-22-850-B-xSF	LED 4' T8	2200	22.00	2200	22.00	2600	34.0
LEDT8-22-840-B-xSF	LED 4' T8	2150	22.00	2150	22.00	2500	34.0
LEDT8-22-835-B-xSF	LED 4' T8	2000	22.00	2000	22.00	2400	34.0
LEDT8-22-830-B-xSF	LED 4' T8	2000	22.00	2000	22.00	2400	34.0

* High Performance DLC qualified models are for Instant Start ballast operation only

LED T8 Performance with different ballast factor Instant Start (IS) ballasts	T8 IS Low Ballast Factor (0.78)		T8 IS Normal Ballast Factor (0.88)		T8 IS High Ballast Factor (1.18)	
	Lumens	System Watts	Lumens	System Watts	Lumens	System Watts
LEDT8-17-850-B-FHF	1525	13.8	1785	16.8	2750	26.5
LEDT8-17-840-B-FHF	1480	13.8	1700	16.8	2670	26.5
LEDT8-17-835-B-FHF	1440	13.8	1683	16.8	2610	26.5
LEDT8-17-830-B-FHF	1380	13.8	1660	16.8	2480	26.5

Note: All specification Information subject to change without notice. Results may vary based on ballast manufacture.

Part number designation:

- xxx

F - Fixed or R - Rotatable locking end caps

S - Standard or H - High Performance

High Performance = DLC qualified models

C - Clear or F - Frosted Lens



Linear LED T8 Lamp

Compatible for use with fluorescent T8 and T12 ballasts

2', 3' and 4' Specification


Installation Instructions:

Quick and Simple - No re-wiring required

Step 1: Turn
Power - OFF




Step 2: Remove
Fluorescent lamp



Step 3: Plug in
Quick-Fit LED lamp




Step 4: Turn
Power - ON




- There are multiple types of ballast designs (also called topologies) used in fluorescent light fixtures. To assure proper LED lamp operation and confirm ballast compatibility try product in the fixture before installing large quantities.
- Suitable for damp locations. Avoid applications where lamp can get wet.
- Operating temperature range between -4°F and 122°F (-20°C and 50°C).
- To meet local and national building safety codes most commercial buildings use light fixtures installed with battery backup fluorescent ballasts to provide temporary lighting in the event of a power loss. The most common style of battery back-up ballast (~ 80% market share) switches out one lamp from the existing ballast and powers the fluorescent lamp when in operation. The ELB Quick-Fit LED direct replacement lamp with multi-operation technology is compatible with these standard fluorescent battery back-up ballast products where most other direct replacement LED lamps are not compatible. Check local and state electrical codes for acceptance of use.


Instant Start T8 Ballast




Program Start Electronic T8 or Magnetic T12 Rapid Start Ballast



Magnetic T12 Choke Style Ballast



OPTIONAL: Remote AC LED Driver
(Standard or Diming model)



Electronic T8 Instant Start ballast	YES	YES
Electronic T8 Program Start ballast	YES	NO
Magnetic T12 ballast	YES	NO
Emergency Ballast (most designs)	YES	NO
External LED dimming driver 120-277VAC operation	YES (available)	?

ENERGY SAVINGS: Operation based on standard 2 lamp F32T8 Electronic Instant Start System with Standard 0.88 Ballast Factor = 58 System Watts. The LED T8 QuickFit = 34 System Watts. Each 2 lamp system saves 24 System Watts or 41.4% Energy Saved

Linear LED T8 Lamp

Compatible for use with fluorescent T8 and T12 ballasts

2', 3' and 4' Specification

Ordering Information:

Model #	Type (Dia.)	Base	Length (Inches)	Color Temp. (K)	CRI	Rated Average Life (hrs)	Beam angle	Input Voltage	*DLC Qualified
LEDT8-8-850-B-xSx	LED T8	G13-bipin	24	5000	82	50,000	270	ballast	
LEDT8-8-840-B-xSx	LED T8	G13-bipin	24	4000	82	50,000	270	ballast	
LEDT8-8-835-B-xSx	LED T8	G13-bipin	24	3500	82	50,000	270	ballast	
LEDT8-8-830-B-xSx	LED T8	G13-bipin	24	3000	82	50,000	270	ballast	
LEDT8-8-850-B-FHF	LED T8	G13-bipin	24	5000	82	50,000	270	ballast	In process
LEDT8-8-840-B-FHF	LED T8	G13-bipin	24	4000	82	50,000	270	ballast	In process
LEDT8-8-835-B-FHF	LED T8	G13-bipin	24	3500	82	50,000	270	ballast	In process
LEDT8-8-830-B-FHF	LED T8	G13-bipin	24	3000	82	50,000	270	ballast	In process
LEDT8-12-850-B-xSx	LED T8	G13-bipin	36	5000	82	50,000	270	ballast	-
LEDT8-12-840-B-xSx	LED T8	G13-bipin	36	4000	82	50,000	270	ballast	-
LEDT8-12-835-B-xSx	LED T8	G13-bipin	36	3500	82	50,000	270	ballast	-
LEDT8-12-830-B-xSx	LED T8	G13-bipin	36	3000	82	50,000	270	ballast	-
LEDT8-17-850-B-xSx	LED T8	G13-bipin	48	5000	83	50,000	270	ballast	-
LEDT8-17-840-B-xSx	LED T8	G13-bipin	48	4000	83	50,000	270	ballast	-
LEDT8-17-835-B-xSx	LED T8	G13-bipin	48	3500	83	50,000	270	ballast	-
LEDT8-17-830-B-xSx	LED T8	G13-bipin	48	3000	83	50,000	270	ballast	-
LEDT8-17-850-B-FHF	LED T8	G13-bipin	48	5000	83	50,000	270	ballast	qualified
LEDT8-17-840-B-FHF	LED T8	G13-bipin	48	4000	83	50,000	270	ballast	qualified
LEDT8-17-835-B-FHF	LED T8	G13-bipin	48	3500	83	50,000	270	ballast	qualified
LEDT8-17-830-B-FHF	LED T8	G13-bipin	48	3000	83	50,000	270	ballast	qualified
LEDT8-22-850-B-xSx	LED T8	G13-bipin	48	5000	83	50,000	270	ballast	-
LEDT8-22-840-B-xSx	LED T8	G13-bipin	48	4000	83	50,000	270	ballast	-
LEDT8-22-835-B-xSx	LED T8	G13-bipin	48	3500	83	50,000	270	ballast	-
LEDT8-22-830-B-xSx	LED T8	G13-bipin	48	3000	83	50,000	270	ballast	-

Note: Lamps operate at 120,277 and 377VAC using the existing T8 electronic instant start ballast, T8 electric program rapid start ballast and T12 magnetic ballast. Lamp wattage and Lumens noted in chart are based on operation with standard T8 Instant Start ballast.

Photometric testing is consistent with IES-LM-79 and tested to L70 requirements.

* DLC qualified for Instant start ballast operation only.

See Warranty for terms and conditions. Information is subject to change without notice.

Part number designation:

- xxx

F - Fixed or R - Rotatable locking end caps

S - Standard or H - High Performance

High Performance = DLC Qualified models

C - Clear or F - Frosted Lens