

MODEL SKU MR16 7W 450LM 2700K GU10 SE-RL5.CI02.1107G

DIMMER COMPATIBILITY LIST				
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY	
		DV-603P	OK	
		DV-603PR	OK	
	L	DV-600P-WH	OK	
		DVELV-300P-WH	OK	
	DIVA	DVW-600PH-WH	NC OK	
		DV-603PH-WH	OK	
		DV-600PH-WH D-600RH-DK	OK NG	
		D-600KH-DK DVCL-153PH	NC OK	
		DV-603PH-WH	OK OK	
		DVCL-153P-WH	NC NC	
		S-600	OK OK	
	LUMEA	LGCL-153CL	NC NC	
 	LOIVIE/	CT-103P-WH	OK	
	ľ	CTCL-153P-WH	NC NC	
		S-600PR-WH	OK	
		S-603P-WH	NC NC	
		SELV-300P-WH	OK	
	ľ	SLV-600-WH	OK OK	
	SKYLARK	S-603PGH-WH	OK OK	
		S-600H-WH	OK	
	ľ	S-10PH	NC NC	
		SCL-153P-WH	NC	
LUTRON		S-600-IV	OK	
EUTKON		S-600-AL	NC NC	
		S-603PH-WH	NC NC	
		TGCL-153PH-WH	OK	
		TGCL-153PLH-WH	OK	
	TOOGLER	TG-600PH-WH	OK OK	
		TG-600PH-IV	OK	
 		MAW-600H-WH	NC	
	MAESTRO	MACL-153M-WH	OK	
		MAELV-600-WH	OK	
		MAW-600H-AL	NC	
	=	D-600PH-DK	OK	
	-	MAW-600	NC	
	-	D-600PH-3CK	NC	
	DIVA C*L	DVWCL-153PH-WH	OK	
	VIVE	MRF2S-6CL-WH	OK	
	CASETA	PD-6WCL-WH	OK	
	SPACER	SPSELV-600M	OK	
	NOVA T	NTELV-300-WH	OK	
	NOVA T	NTLV-600-277-WH	OK	
	RADIO RA2	RRD-6CL-WH	OK	
	ARIADNI	AYCL-153P-WH	OK	
	-	D-600R-WH	OK	
	-	D-600R-IV	NC	
	DECORA	R62-6674-P0W	OK	
<u> </u>	-	6683-IW	NC	
	-	6631-LA	OK	
<u> </u>	-	IPI06	NC	
<u> </u>	-	S-600P-WH	NC	
<u> </u>	-	6684	OK	
LEVITON	-	6683	NC	
	-	NO.6672	NC NC	
<u> </u>	-	603-6631-A	OK	
	-	6631-A	OK	
	-	NO.IPL06	NC	
	-	IPI10-1LZ	NC	
	-	6683-10Z	NC	
	-	IPI06-1LZ	NC NC	
	-	NO.6631	NC	
ТОР	-	HCL453PTC	OK	
	-	HCL453PW	OK	
AH	-	SDM/600	OK	
GE	-	18024	NC	
ALMOND	-	LUXDM600-12	OK	

## DIMMER COMPATIBILITY

OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

## 90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.

  2) The results may be different for each application depending on the installation conditions.

  3) 90+ Lighting reccomends to perform a previous test before the installation to verify the dimmer compatibility.

  4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.

  For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.

