

Mini Springs

Smallest size CFLs ever! Mini Springs fit where other lamps are too large, while giving off an incredible amount of light for their size.

SpringLamps®

With Quickstart Technology and fast run-up time, our SpringLamps are ideal for a variety of applications including: bare bulb fixtures, chandeliers, ceiling fixtures, desk lamps, floor lamps, outdoor lights, table lamps, recessed cans and wall sconces.

Fresh²Ti

Fresh²Ti is a revolutionary product that breaks down odors while providing energy-efficient light. Simply turn on your light and Fresh²Ti begins eliminating odors in just 10 minutes!

ITEM NUMBER	ITEM DESCRIPTION	UNIT/BALLAST WATTS	LAMP WATTS	INCANDESCENT COMPARISON (WATTS)	INITIAL LUMENS	CCT (KELVIN)	CRI	MOL/HEIGHT (INCHES)	DIAMETER/WIDTH (INCHES)	REPLACEMENT BRACKET	REPLACEMENT LAMP	BASE TYPE
MINI MINI, ELECTRONIC, NPF, 8,000 HOUR, <150% THD												
28902	2 Watt Mini-SpringLamp	2	N/A	15	150	2700	82	3.00	1.25	N/A	N/A	E26
28902C	2 Watt Mini-SpringLamp	2	N/A	15	150	2700	82	3.00	1.25	N/A	N/A	Candelabra
28902T	2 Watt Tall Mini-Spring Lamp	2	N/A	15	150	2700	82	3.13	1.25	N/A	N/A	E26
28902TC	2 Watt Tall Mini-Spring Lamp	2	N/A	15	150	2700	82	3.10	1.20	N/A	N/A	Candelabra
28904	4 Watt Mini-SpringLamp	4	N/A	25	250	2700	82	3.00	1.50	N/A	N/A	E26
28904C	4 Watt Mini-SpringLamp	4	N/A	25	250	2700	82	3.10	1.50	N/A	N/A	Candelabra
28904T	4 Watt Tall Mini-Spring Lamp	4	N/A	25	250	2700	82	3.60	1.25	N/A	N/A	E26
28904TC	4 Watt Tall Mini-Spring Lamp	4	N/A	25	250	2700	82	3.50	1.20	N/A	N/A	Candelabra
MINI SPRINGLAMPS, ELECTRONIC, NPF, 10,000 HOUR, <150% THD												
28909	9 Watt Mini-SpringLamp	9	N/A	40	550	2700	82	3.60	1.90	N/A	N/A	E26
28913	13 Watt Mini-Spring Lamp	13	N/A	60	900	2700	82	3.90	1.90	N/A	N/A	E26
*12000 Lamp Life												
28918	18 Watt Mini-Spring Lamp	18	N/A	75	1200	2700	82	4.40	2.30	N/A	N/A	E26
28923	23 Watt Mini-Spring Lamp	23	N/A	100	1600	2700	82	4.70	2.40	N/A	N/A	E26
28923FS	23 Watt Mini-Spring Lamp Full Spectrum	23	N/A	100	1200	5500	90	4.70	2.40	N/A	N/A	E26
28927M	27 Watt Mini-Spring Lamp	27	N/A	100	1850	2700	82	5.10	2.40	N/A	N/A	E26
19032	14/19/32 Watt 3-Way SpringLamp	14 19 32	N/A N/A N/A	40 75 150	450 1100 1950	2700	82	6.80	2.40	N/A	N/A	E26
SPRINGLAMPS, ELECTRONIC, NPF, 10,000 HOUR, <150% THD												
28932	32 Watt SpringLamp	32	N/A	120	2100	2700	82	6.10	2.70	N/A	N/A	E26
28932H	32 Watt SpringLamp Mogul Base	32	N/A	120	2200	2700	82	6.60	2.80	N/A	N/A	Mogul
28942	42 Watt SpringLamp	42	N/A	150	2800	2700	82	7.00	2.80	N/A	N/A	E26
28942H	42 Watt SpringLamp Mogul Base	42	N/A	150	2800	2700	82	7.50	2.80	N/A	N/A	Mogul
28968	68 Watt SpringLamp	68	N/A	300	4200	2700	82	9.50	4.10	N/A	N/A	E26
28968H	68 Watt SpringLamp Mogul Base	68	N/A	300	4200	2700	82	9.90	4.10	N/A	N/A	Mogul
28930BD	30 Watt Base Down SpringLamp	30	N/A	120	2100	2700	82	5.40	3.00	N/A	N/A	E26
28942BD	42 Watt Base Down SpringLamp	42	N/A	150	2650	2700	82	5.70	2.70	N/A	N/A	E26
SPRINGLAMPS, ELECTRONIC, NPF, 10,000 HOUR, 277V, <150% THD												
28927H277	27 Watt SpringLamp 277 Volt, Mogul Base	27	N/A	100	1950	2700	82	6.20	2.80	N/A	N/A	Mogul
28932H277	32 Watt SpringLamp 277 Volt, Mogul Base	32	N/A	120	2200	2700	82	6.60	2.80	N/A	N/A	Mogul
28942H277	42 Watt Base Down 277 Volt, Mogul Base	42	N/A	150	2800	2700	82	7.50	2.80	N/A	N/A	Mogul
28968H277	68 Watt Base Down 277 Volt, Mogul Base	68	N/A	300	4250	2700	82	9.90	4.10	N/A	N/A	Mogul

= Energy Star