

ProLED Product Code & Product Number	
PAR38/11WW/FL/LED(80010)	PAR38/11WW/NFL/LED(80012)
PAR38FL16/827/LED(80040)	PAR38SP16/830/LED(80042)
PAR38FL16/830/LED(80032)	PAR38NFL16/830/LED(80034)
PAR38FL16/840/LED(80044)	
PAR38FL16/850/LED(80036)	
PAR38SP20/827/LED(80046)	PAR38NFL20/827/LED(80048)
PAR38SP20/830/LED(80052)	PAR38NFL20/830/LED(80054)
PAR38FL20/840/LED(80058)	PAR38NFL20/850/LED(80062)
PAR38SP20/850/LED(80060)	

Max Lamps per 600W Dimmer		
Lamp type	In-rush	# of Lamps
11W	68W	8
16W	115W	5
20W	115W	5

Brand	Model	Load	Type	Compatibility	Max Lamps	Compatibility	Max Lamps	Compatibility	Max Lamps
Lutron	"Lutron C-L" ANALOG DIMMERS	150W	CFL/LED	YES	8	YES	5	YES	5
	AY-600P/CN-600P/S-600P/Q-600P	600W	INC	YES	8	YES	5	YES	5
	D-603PH	600W	INC	YES	8	YES	5	YES	5
	DV-600PH/D-600PH	600W	INC	YES	8	YES	5	YES	5
	DV-603PG/TG-603PGH	600W	INC	YES	8	YES	5	YES	5
	DVELV-300P/SELV-300P	300W	ELV	YES	4	YES	2	YES	2
	GL-600H	600W	INC	YES	8	YES	5	YES	5
	NELV-450	450W	ELV	YES	6	YES	3	YES	3
	TG-600PNLH	600W	INC	YES	8	NO	X	NO	X
	MRF2-3PD-1	300W	INC	YES	4	YES	2	YES	2
	MRF2-6ND-120	600W	MLV	YES	8	YES	5	YES	5
	MRF2-6ELV-120	600W	ELV	YES	8	YES	5	YES	5
	MAELV-600/VTELV-600	600W	ELV	YES	8	YES	5	YES	5
	AYLV-600P/DVLV-600P/NTLV-600/NLV-600	600W	MLV	YES	8	YES	5	YES	5
	TT-300NLH	300W	INC	YES	4	YES	2	YES	2
Leviton	RRD-10ND	1000W	INC	YES	14	YES	8	YES	8
	6613-P	450W	MLV	YES	6	YES	3	YES	3
	6633-P	600W	INC	YES	8	YES	5	YES	5
	6683	600W	INC	YES	8	NO	X	NO	X
	6684	600W	INC	YES	8	YES	5	YES	5
	RP106-LAW	600W	INC	YES	8	YES	5	YES	5
	6674	150W	CFL/LED	YES	8	YES	5	YES	5
	IPL06	150W	CFL/LED	YES	8	YES	5	YES	5
	IPE04	300W	ELV	YES	4	YES	2	YES	2
	6615	300W	ELV	YES	4	YES	2	YES	2
	6681	600W	INC	YES	8	YES	5	YES	5
Pass & Seymour	IPI06	600W	INC	YES	8	YES	5	YES	5
	CD703-PW	700W	INC	YES	10	YES	6	YES	6
	CDLV703-PW	700W	MLV	YES	10	YES	6	YES	6
	DCL453-PTC	450W	CFL/LED	YES	8	NO	X	NO	X
	D703-PTC	700W	INC	YES	10	YES	6	YES	6
	DRD4	600W	INC	YES	8	YES	5	YES	5
	DLV703	700W	MLV	YES	10	YES	6	YES	6

ProLED lamps may function on dimmer models not listed above.
Actual performance of the lamp and dimmer configuration may vary.
Specifications subject to change without notice.