

Warm Dim

9W LED G25 3000K - 1800K FILAMENT MILKY WARM DIM

Item# 776404

Ordering Code LED9G25/30K-18K/WMDM/FIL/M

UPC 739698764047

- **SET THE RIGHT MOOD:** Smoothly shifting in color temperature from 3000 kelvin (soft white light) to 1800 kelvin (candlelight), these bulbs are perfect for any room where you want the light to go from bright task lighting to warm, cozy moods.
- **MULTIPLE USES:** This round decorative G25 bulb suits any style and is compatible with any E26 screw base fixture, ideal for indoor or outdoor lamps, pendants, chandeliers and open fixtures where the round bulb is fully visible, and with a wet rating, also look great above a bathroom vanity.
- Fully Dimmable and works with most dimmer switches
- **CLEAN, CRISP COLOR:** Discover authentic hues with our remarkable Color Rendering Index of 90 (CRI90) and light up your living spaces with true-to-life colors, embracing the beauty of natural lighting.
- 5 year Limited Lifetime Warranty



Width	Height	Length
3.270 in	5.310 in	3.270 in



Technical Specifications			
Avg Hours	15000	Item #	776404
Base	E26	Lumens	800
Bulb Type	G25	M.O.D	2.354 in
CBCP	0	M.O.L	4.123 in
CCT Color	3000K-1800K	Outer Carton Qty	40
Dimmable	Y	Outer Carton UPC	40739698764045
Enclosed Rated	Y	Safety Rated	UL
Energy Star	N	Safety Rating Type	WET
Equivalent	60	Title 20	Y
Finish	Milky	Title 24	N
Individual Qty	1	Volts	120
Individual UPC	739698764047	Warranty Years	5
Inner Carton Qty	10	Watts	9
Inner Carton UPC	10739698764044		



Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name:	776400	776404	776405
Item Number:	LED9A19/30K-18K/WMDM/FIL/M	LED9G25/30K-18K/WMDM/FIL/M	LED9ST18/30K-18K/WMDM/FIL/M
Ordering Code:			
Item Number:			
Ordering Code:			

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
					Recommended Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IPI06	Good	1	6	Not smooth dimming
		SureSlide	6633-P	Best	1	6	Dims down to 1%
		Vizia	VPI06-1LZ	Best	1	6	Dims down to 1%
	Lutron	Toggler	TG-600	Best	1	6	Dims down to 1%
		Lumea	LGCL-600	Best	1	6	Dims down to 1%
		Diva	DV-600	Best	1	6	Dims down to 1%
		Skylark	S-600	Best	1	6	Dims down to 1%
		Maestro	MAW-600	Good	4	6	Dims down to 1%
	Legrand	Titan	CD703-PW	Good	4	6	Dims down to 1%
		Harmony	D703-PTC	Good	3	6	Dims down to 1%
Harmony		H703-PTC	Good	3	6	Dims down to 1%	
CFL/LED	Leviton	IllumaTech	IPL06	Best	1	6	Dims down to 1%
		Sureslide	6674	Best	1	6	Dims down to 1%
		Decora	6672	Best	1	6	Dims down to 1%
		Decora Slide	DSL06-1LZ	Best	1	6	Dims down to 1%
	Lutron	Skylark	CTCL-153	Best	1	6	Dims down to 1%
		Sunnata	STCL-153	Best	1	6	Dims down to 1%
		Diva	DVCL-153PL	Best	1	6	Dims down to 1%
		Maestro	MAEL-153MLH	Best	1	6	Dims down to 1%
		Skylark	SCL-153P	Best	1	6	Dims down to 1%
		Toggler	TGCL-153PH	Best	1	6	Dims down to 1%
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 1%
	Legrand	Harmony	DCL453-PTC	Best	1	6	Dims down to 1%
		Radiant	RHCL453PW	Best	1	6	Dims down to 1%
		Adorne Paddle	ADPD453LM2	Best	1	6	Dims down to 3%
Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	6	Dims down to 1%
		IllumaTech	IPE04	Not compatible	1	6	Reverse dimming with 1-6
		Decora	6615-P	Not compatible	1	6	Reverse dimming with 1-6
	Lutron	Skylark Countour	CTELV-303P	Best	1	6	Dims down to 1%
		Diva	DVELV-300P	Best	1	6	Dims down to 1%
		Maestro	MAELV-600	Best	1	6	Dims down to 1%
		Skylark	SELVB-300P	Best	1	6	Dims down to 1%
		VIERTI	VTEL-600M-W	Best	1	6	Dims down to 1%
Legrand	Scene Director	SCELV	Best	1	6	Dims down to 5%	
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Best	1	6	Dims down to 1%
		Decora	6613-P	Best	1	6	Dims down to 1%
	Lutron	Maestro	MALV-600	Not compatible	1	6	Doesn't turn on with 1-6
		Harmony	DLV703-PW	Good	2	6	Dims down to 1%
	Legrand	Titan	CDLV703-PW	Good	2	6	Dims down to 1%
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims down to 1%
	Leviton	Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	Dims down to 1%
	Leviton	Decora Smart WiFi Technology	DW1KD	Best	1	6	Dims down to 1%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	Dims down to 1%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6	Dims down to 1%
	Deako	Single pole Smart dimmer	DS-CD1M-WHMC-UCV	Bad	1	6	Dims down to 1%, It turn on with a flash at HE
	GE	Z WAVE	ZW3005	Best	1	6	Dims down to 1%
Universal	Legrand	Adorne Softap	ADTP703TU	Best	1	6	Dims down to 10%
		Miro Decorator	DRD4-W	Not compatible	1	6	Flicker at HE with 1-6
		Harmony	H703PTUTC	Best	1	6	Dims down to 10%
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 1%
		Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims down to 1%
	Cooper	Decorator	DAL06P-C2-K-L	Best	1	6	Dims down to 1%
		Skye	SAL06P-W-K-L	Best	1	6	Dims down to 1%

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
 †May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	