

A-Type Dimmable

9W LED A19 60W EQUIV PREFERRED DIMMABLE
2700K E26 120V - 4PK

Item# 774253

Ordering Code LED9A19/PF60W/927/D/2/4P

UPC 739698777047

- A19 LED bulb with an E26 base in a Frost Finish
- Damp location rated and long-lasting.
- Commonly used in ceiling fixtures and portables.
- Fully Dimmable and works with most dimmer switches
- Suitable for fully enclosed fixtures.
- Long lasting energy efficient LED lighting, lasts up to 15,000 hours.
- 2 Year Limited Warranty
- 2 year Limited Warranty



Width	Height	Length
4.720 in	2.560 in	10.240 in



Technical Specifications			
Avg Hours	15000	Inner Carton UPC	10739698777044
Base	E26	Item #	774253
Beam Angle(°)	220	Lumens	800
Bulb Type	A19	M.O.D	2.360 in
CCT Color	2700K	M.O.L	4.250 in
Color	Warm White Light	Outer Carton Qty	1
CRI	90	Outer Carton UPC	40739698777045
Dimmable	Y	Safety Rated	UL
Enclosed Rated	Y	Safety Rating Type	DAMP
Energy Star	N	Title 20	Y
Equivalent	60	Title 24	N
Finish	Frost	Volts	120
Individual Qty	4	Warranty Years	2
Individual UPC	739698777047	Watts	9
Inner Carton Qty	3		



Tested Unit Item Number: 774265 Tested Unit Ordering Code: LED9A19/PF60W/950/D/2/1P Related Item Number: 774253 Related Ordering Code: LED9A19/PF60W/927/D/2/4P Related Item Number: 774254 Related Ordering Code: LED9A19/PF60W/930/D/2/4P	Related Item Number: 774255 Related Ordering Code: LED9A19/PF60W/940/D/2/4P Related Item Number: 774256 Related Ordering Code: LED9A19/PF60W/950/D/2/4P Related Item Number: 774257 Related Ordering Code: LED9A19/PF60W/927/D/2/25P	Related Item Number: 774258 Related Ordering Code: LED9A19/PF60W/930/D/2/25P
--	---	---

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
					Recommended Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	a IllumaTech	IPI06	Good	1	6	Not smooth, flickers whil dimming, dims completely
		b SureSlide	6633-P	Best	1	6	Dims completely
		c Vizia	VPI06-1LZ	Best	1	6	Dims completely
	Lutron	d Toggler	TG-600	Best	1	6	Dims completely
		e Lumea	LGCL-600	Best	1	6	Dims completely
		f Diva	DV-600	Best	1	6	Dims completely
		g Skylark	S-600	Best	1	6	Dims completely
	Legrand	h Maestro	MAW-600	Not Compatible	1	6	
		i Titan	CD703-PW	Bad	2	6	Not compatible with 1, dims completely
		j Harmony	D703-PTC	Bad	1	6	Not compatible with 1, not smooth, jumps, dims completely
k Harmony		H703-PTC	Bad	1	6	80% MAX with 1, dims completely	
CFL/LED	Leviton	l IllumaTech	IPL06	Best	1	6	Dims completely
		m Sureside	6674	Best	1	6	Dims completely
		n Decora	6672	Best	1	6	Dims to 2%
		o Decora Slide	DSL06-1LZ	Best	1	6	Dims completely
	Lutron	p Skylark	CTCL-153	Best	1	6	Dims to 4%
		q Diva	DVCL-153PL	Best	1	6	Dims to 4%
		r Maestro	MACL-153MLH	Best	1	6	Dims completely
		s Skylark	SCL-153P	Best	1	6	Dims completely
		t Toggler	TGCL-153PH	Best	1	6	Dims completely
		u Radio RA	RA2RR-6CL-PD	Good	1	6	Not smooth, slight flicker, dims completely
	Legrand	v Harmony	DCL453-PTC	Best	1	6	Dims to 3%
		w Harmony	HCL453PTC	Best	1	6	Dims to 3%
		x Adorne Paddle	ADPD453LM2	Bad	1	6	Dims to 11%
Electronic Low Voltage	Leviton	y Vizia	VPE04	Good	1	6	Not smooth, jumps, dims completely
		z IllumaTech	IPE04	Not Compatible	1	6	
	Lutron	aaa Decora	6615-P	Not Compatible	1	6	
		ab Skylark Countour	CTELV-303P	Good	1	6	HE dead travel (20%), dims completely
		ac Diva	DVELV-300P	Best	1	6	Dims completely
		ad Maestro	MAELV-600	Best	1	6	Dims completely
		ae Skylark	SELVB-300P	Good	1	6	HE dead travel (20%), dims completely
		af VIERTI	VTEL-600M-W	Best	1	6	Dims completely
		ag Scene Director	SECLV	Bad	1	6	Flickers @ MAX, dims to 1%
Magnetic Low Voltage	Leviton	ah Vizia	VPM-06	Good	1	6	90% MAX with 1, dims completely
		ai Decora	6613-P	Best	1	6	Dims completely
	Lutron	aj Maestro	MALV-600	Not Compatible	2	6	Not compatible with 1 or 6
		ak Harmony	DLV703-PW	Best	1	6	Dims completely
		al Titan	CDLV703-PW	Best	1	6	Dims completely
Smart Dimmer	Leviton	am Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims completely
		an Decora Smart Z-Wave Technology	DZ6HD	Good	1	6	Not smooth, jumps while operating, dims completely
	Lutron	ao Decora Smart WiFi Technology	DW1KD	Best	1	6	Dims completely
		ap Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Good	1	6	Dims to 10%
	GE	aq Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	Dims to 8%
		ar Z WAVE	ZW3005	Best	1	6	Dims completely
Universal	Legrand	as Adorne Softap	ADTP703TU	Bad	1	6	Dims to 12%
		at Miro Decorator	DRD4-W	Good	1	6	Not smooth, jumps, dims to 6%
		au Harmony	H703PTUTC	Not Compatible	1	6	Dims to 35%
		av Adorne Whisper	ADWR700MMTUW2	Good	1	6	95% @ MAX, dims completely
		aw Adorne Touch	ADTH700MTUM2	Good	1	6	95% @ MAX, dims completely
		ax Decorator	DAL06P-C2-K-L	Best	1	6	Dims completely
	Cooper	ay Skye	SAL06P-W-K-L		1	6	

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
 *May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	Description
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (HE) Dead Travel Low End (LE) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.